LUCASACS

LONDON 600RM

Remote Microphone

Features

The LONDON-600RM remote microphone or call station is EN54-16 certified and designed exclusively for LONDON-600 public address & voice evacuation system. The remote microphone is used for business and commercial live announcement to selected zones or all zones. The remote microphone is designed of 12 zone buttons with busy & working indicators. One or multiple external 12 zone expansion keypad LONDON 12KD could be cascaded together for up to 120 zone operation. Up to 32 units of remote microphone could be connected to the voice evacuation system via standard, shielded CAT-6 cable and RJ45 connectors in a redundancy loop up to 600 meters. The talk button maybe a PTT or lock type pre-set by the dipswitch on the rear of the microphone. Green LED indicates the microphone and zone active status. The remote microphone is 24VDC powered by the LONDON 600 controller. The voice evacuation system is strictly follow the Construction products Regulation (EU) No 305/2011: EN54-16:2008 Voice Alarm Control and Indicating Equipment.

• Remote microphone or call station of voice evacuation system LONDON-600.

- EN54-16 Certified fireman's microphone.
- Business & commercial zone live announcement use.
- Multiple zone, single zone & all zone paging.
- Each microphone of 12 zone capacity.
- Up to 120 zones by cascaded the zone keypad LONDON-12KD.
- Support 32 remote microphones of loop redundancy connection.
- The remote microphone unit is fully real time monitored.
- Support PPT and lock type two modes.
- Shielded CAT-6 cable up to 600 meters.
- Power supply from LONDON-600 controller.



Technical Specifications

Description	Remote Microphone
Power Consumption	3W
Zone Capacity	12 Zones
System Capacity	32 Remote microphones
Line Inputs	350mV, 10kΩ
Mic Input	5mV, 600Ω
Frequency Response	80Hz~16kHz
THD	<1% at RMS,1KHz
S/N Ratio	>70dB
Operating Temp	-20°C to +70°C
Power Supply	DC24V, ±20%
Humidity	<95% no condensation
Dimension	256(W)×149(H)×52(D) mm
Weight	1.5kg