

## WS400 - WS400AN - WS400AMP

### 4 Channel Antenna Splitter

#### Features

Ultra-wide band 450-950 MHz .

Compatible with up to 4 UHF true diversity receivers to one set of antenna.

Adopts the latest wide dynamic range and low noise component.

Advanced circuit design featuring very low inter-modulation distortion and eliminates the spurious interference. BNC antenna connectors.

Allows daisy-chain antenna dividers for more receivers.

Active directional antenna design with high / low gain can be selected supply (DC12V/1A) can support the usage of four receivers at the same time.



#### Technical Specifications

<b>Frequency Range:</b>	450-950MHz
<b>Output Gain:</b>	10dB ± 1dB
<b>IIP3:</b>	+14dBm
<b>Noise Figure:</b>	< 2dB
<b>Impedance:</b>	50Ω
<b>Connector:</b>	BNC
<b>Antenna Power Supply:</b>	8V/100mA DC
<b>Output Power Supply:</b>	Each Channel: 12V/1000mA DC
<b>Power Supply:</b>	110-240V AC 50/60 Hz