

## DM2412D

### 24 INPUT DIGITAL MIXER

#### Features

You can set up many projects with ease and perfect sound with this digital mixer specially produced by LUCASACS DM2412D to hear the perfect sound. Our mixer, which has a touch screen and is completely digital, is specially designed for meeting rooms, conference halls, schools, churches and live music. It can be easily used in small and medium sized projects, optional DANTE programming.



#### Technical Specifications

Feature	Specification
Developed based on Linux	No fear of viruses, safer and more stable operation, Optional Android and IOS programme
Optional DANTE Programmer	Yes
Inputs	24/12 MIC/Line inputs, 4 combo, 2 stereo input, 1 digital input: optical/sound card, MP3
MIC Input Gain	Digital gain participation storage
+48V Phantom Power	MIC channels can be turned on and off independently
Built-in Processing	Noise gate, compressor, high and low pass, 7-band parametric EQ equalization, time delay, channel pan balance adjustment
Multi-Function Knob	24 bits, 48kHz MDS.Quantum
Motorized Faders	13 TPDD100MM motorized faders with signal and peak light
Outputs	8 signal outputs (main output L, R, 4 AUX outputs, 2 group outputs, 1 monitoring output)
Output Processing	High and low pass filtering, 12-band parametric EQ equalization, compressor, delay, phase
Display	6.8-inch color 1024 x 600 resistive touch display